

Electromagnetic field theory

Statics

Coulombs law

The force F on a point charge q_1 at the point \mathbf{r}_1 caused by a point charge q_2 at the point \mathbf{r}_2

$$F = \frac{q_1 q_2}{4\pi\epsilon_0 |r_1 - r_2|^2} \frac{(r_1 - r_2)}{|r_1 - r_2|}$$

Electric Field Strength

From a point charge q in \mathbf{r}'

$$\mathbf{E}(\mathbf{r}) = \frac{q}{4\pi\epsilon_0 R^2} \mathbf{e}_R$$

From charge distribution

$$\mathbf{E}(\mathbf{r}) = \int \frac{1}{4\pi\epsilon_0 R^2} \mathbf{e}_R dq(\mathbf{r}'),$$

$$dq(\mathbf{r}') = \begin{cases} \rho_{tot}(\mathbf{r}') dv' = \rho(\mathbf{r}') + \rho_p(\mathbf{r}') dv' \\ \rho_{tot,s}(\mathbf{r}') dS' = \rho_s(\mathbf{r}') + \rho_{p,s}(\mathbf{r}') dS' \\ \rho_l(\mathbf{r}') dl' \end{cases}$$

From point dipole $\mathbf{p} = p\mathbf{e}_z$

$$\mathbf{E}(\mathbf{r}) = \frac{p}{4\pi\epsilon_0 r^3} (2\cos(\theta)\mathbf{e}_r + \sin(\theta)\mathbf{e}_\theta)$$

From line charge ρ_l

$$\mathbf{E}(\mathbf{r}) = \frac{\rho_l}{2\pi\epsilon_0 r_c} \mathbf{e}_{r_c}$$

From dipole line $\mathbf{p}_l = p_l \mathbf{e}_x$

$$\mathbf{E}(\mathbf{r}) = \frac{p_l}{2\pi\epsilon_0 r_c^2} (\cos(\varphi)\mathbf{e}_{r_c} + \sin(\varphi)\mathbf{e}_\varphi)$$

Electrical Potential

$$\mathbf{E} = -\nabla V$$

From pointsource q in \mathbf{r}'

$$V(\mathbf{r}) = \frac{q}{4\pi\epsilon_0 R}$$

From charge distribution

$$V(\mathbf{r}) = \int \frac{1}{4\pi\epsilon_0 R} dq(\mathbf{r}')$$

From point dipole $\mathbf{p} = p\mathbf{e}_z$

$$V(\mathbf{r}) = \frac{\mathbf{p} \cdot \mathbf{r}}{4\pi\epsilon_0 r^3} = \frac{p \cos(\theta)}{4\pi\epsilon_0 r^2}$$

From line charge ρ_l

$$V(\mathbf{r}) = \frac{\rho_l}{2\pi\epsilon_0} \ln\left(\frac{1}{r_c}\right)$$

From dipole line $\mathbf{p}_l = p_l \mathbf{e}_x$

$$V(\mathbf{r}) = \frac{p_l}{2\pi\epsilon_0} \frac{\cos(\varphi)}{r_c}$$

Electrical flow density

Where \mathbf{D} is defined by $\nabla \mathbf{D} = \rho$

Gauss law, where \mathbf{e}_n is the unit normal to the volume surface pointing outwards \mathbf{P} , \mathbf{E} and \mathbf{D} :

$$\begin{cases} \mathbf{D} = \epsilon_0 \mathbf{E} + \mathbf{P} & \text{(valid generally)} \\ \mathbf{D} = \epsilon_r \epsilon_0 \mathbf{E} \end{cases}$$

Polarization Charge

$$\rho_p = -\nabla \cdot \mathbf{P} \quad \text{space charge density}$$

$$\rho_{p,s} = \mathbf{e}_{n1} \cdot (\mathbf{P}_1 - \mathbf{P}_2) \quad \text{surface charge density}$$

where the unit normal \mathbf{e}_{n1} is directed from 1 to 2.

Boundary Conditions

$$\begin{cases} E_t \text{ continuous} \\ \rho_s = \mathbf{e}_{n2} \cdot (\mathbf{D}_1 - \mathbf{D}_2) \end{cases}$$

where ρ_s is free surface charge density and \mathbf{e}_{n2} is directed from volume 2 to volume 1.

Electrostatic Energy

$$W_e = \frac{1}{2} \sum_i Q_i V_i$$

$$W_e = \frac{1}{2} \int \rho V dv$$

$$W_e = \frac{1}{2} \int \mathbf{E} \cdot \mathbf{D} dv$$

Maxwell's voltage

$$|\mathbf{T}| = \frac{1}{2} \mathbf{E} \cdot \mathbf{D} \quad \mathbf{E} \text{ is a bisector to } \mathbf{e}_n \text{ and } \mathbf{T}$$

Torque on Electrical Dipole

$$\mathbf{T}_e = \mathbf{p} \times \mathbf{E}$$

DC Current

Current Density

$$I = \int \mathbf{J} \cdot \mathbf{e}_n dS$$

Conservation Equation

$$\Delta \cdot \mathbf{J} + \frac{\partial \rho}{\partial t} = 0$$

$$\oint \mathbf{J} \cdot \mathbf{e}_n dS = -\frac{dQ}{dt}$$

Conductivity

$$\mathbf{J} = \sigma \mathbf{E}$$

Effect

$$P = \int \mathbf{J} \cdot \mathbf{E} dv$$

Boundary Conditions

$$\begin{cases} \mathbf{e}_{n2} \cdot (\mathbf{J}_1 - \mathbf{J}_2) = 0 & \text{(no surface current)} \\ \mathbf{E}_{t1} = \mathbf{E}_{t2} \end{cases}$$

Time Constant

$$RC = \frac{\epsilon_r \epsilon_0}{\sigma}$$

Analogy Elektrostatics - DC Current

\mathbf{E}, V	\mathbf{E}, V
\mathbf{D}	\mathbf{J}
$\epsilon_r \epsilon_0$	σ
Q	I
C	G

Magnetostatics

Magnetic Flow Density

From point dipole $\mathbf{m} = m \mathbf{e}_z$:

$$\mathbf{B}(\mathbf{r}) = \frac{\mu_0 m}{4\pi r^3} (2 \cos \theta \mathbf{e}_r + \sin \theta \mathbf{e}_\theta)$$

From current density $\mathbf{J}_{tot}(\mathbf{r}')$:

$$\mathbf{B}(\mathbf{r}) = \frac{\mu_0}{4\pi} \int \frac{\mathbf{J}_{tot}(\mathbf{r}') \times \mathbf{e}_R}{R^2} dv'$$

where $\mathbf{J}_{tot} = \mathbf{J} + \mathbf{J}_m$. From current line:

$$\mathbf{B}(\mathbf{r}) = \frac{\mu_0}{4\pi} \int \frac{I d\mathbf{l}' \times \mathbf{e}_R}{R^2}$$

From circular thread loop:

$$\mathbf{B}(x=0, y=0, z) = \frac{\mu_0 I}{2} \frac{b^2}{(b^2 + z^2)^{3/2}} \mathbf{e}_z$$

From coil:

$$\mathbf{B} = \frac{\mu_0 N I}{\ell} \frac{\cos(\alpha_2) - \cos(\alpha_1)}{2} \mathbf{e}_z$$

From long straight current path:

$$\mathbf{B}(\mathbf{r}) = \frac{\mu_0 I}{2\pi r_c} \mathbf{e}_\varphi$$

Vector Potential

$$\mathbf{B} = \nabla \times \mathbf{A}$$

From current density $\mathbf{J}_{tot}(\mathbf{r}')$:

$$\mathbf{A}(\mathbf{r}) = \frac{\mu_0}{4\pi} \int \frac{\mathbf{J}_{tot}(\mathbf{r}')}{R} dv'$$

From current line:

$$\mathbf{A}(\mathbf{r}) = \frac{\mu_0}{4\pi} \int \frac{I dl'}{R}$$

From long straight current path:

$$\mathbf{A} = \frac{\mu_0 I}{2\pi} \ln\left(\frac{1}{r}\right) \mathbf{e}_z$$

From point dipole :

$$\mathbf{A} = \frac{\mu_0}{4\pi} \frac{\mathbf{m} \times \mathbf{r}}{r^3}$$

Magnetic Flow

$$\Phi = \int \mathbf{B} \cdot \mathbf{e}_n dS = \oint \mathbf{A} \cdot d\mathbf{l}$$

Linked Flow

$$\Lambda = N\Phi$$

Self-Inductance and Mutual Inductance

$$\Lambda_1 = L_1 I_1 + M I_2$$

$$\Lambda_2 = L_2 I_2 + M I_1$$

Magnetic Field Strength

Amperes Law:

$$\oint \mathbf{H} \cdot d\mathbf{l} = \int \mathbf{J} \cdot \mathbf{e}_n dS = I_{\text{inside}}$$

Connection between magnetization \mathbf{M} , \mathbf{B} and \mathbf{H} :

$$\begin{cases} \mathbf{B} = \mu_0(\mathbf{H} + \mathbf{M}) & \text{(holds generally)} \\ \mathbf{B} = \mu_r \mu_0 \mathbf{H} \end{cases}$$

Equivalent Current Density

$$\mathbf{J}_m = \nabla \times \mathbf{M} \quad \text{volume current density}$$

$$\mathbf{J}_m = \nabla \times \mathbf{M} \quad \text{surface current density}$$

Boundary Conditions

$$\begin{cases} \mathbf{e}_{n2} \times (\mathbf{H}_1 - \mathbf{H}_2) = \mathbf{J}_s \\ \mathbf{B}_n \text{ Continuous} \end{cases}$$

Scalar Potential

From magnetic dipole \mathbf{m} :

$$V_m = \frac{1}{4\pi} \frac{\mathbf{m} \cdot \mathbf{e}_R}{R^2}$$

Magnetic Pole Density

$$\begin{cases} \rho_m = -\nabla \cdot \mathbf{M} & \text{volume pole density} \\ \rho_{m,s} = \mathbf{e}_{n1} \cdot (\mathbf{M}_1 - \mathbf{M}_2) & \text{surface pole density} \end{cases}$$

Magnetic Force Law

$$d\mathbf{F}_m = I d\mathbf{l} \times \mathbf{B}$$

Magnetic moment for current loop

$$\mathbf{m} = \int I \mathbf{e}_n dS$$

Torque on Magnetic Moment

$$\mathbf{T}_m = \mathbf{m} \times \mathbf{B}$$

Maxwell's Voltage

$$|\mathbf{T}| = \frac{1}{2} \mathbf{B} \cdot \mathbf{H} \quad \mathbf{B} \text{ is a bisector to } \mathbf{e}_n \text{ and } \mathbf{T}$$

Magnetic Energy

$$W_m = \frac{1}{2} \int \mathbf{J} \cdot \mathbf{A} dv = \frac{1}{2} \int \mathbf{B} \cdot \mathbf{H} dv = \frac{1}{2} \sum_i \sum_j L_{ij} I_i I_j$$

Two coils:

$$W_m = \frac{1}{2} L_1 I_1^2 + \frac{1}{2} L_2 I_2^2 + M I_1 I_2$$

Reluctance

$$R = \frac{1}{\mu_r \mu_0 S}$$

Electromagnetic Fields

Induced emk

$$\mathcal{E} = \oint (\mathbf{E} + \mathbf{v} \times \mathbf{B}) \cdot d\mathbf{l}$$

$$\mathcal{E} = -\frac{d\Phi}{dt}$$

$$\mathcal{E} = -\frac{d\Lambda}{dt} \quad (\text{coil with multiple turns})$$

Maxwell's equations

$$\nabla \times \mathbf{E} = -\frac{\partial \mathbf{B}}{\partial t}$$

$$\nabla \times \mathbf{H} = \mathbf{J} + \frac{\partial \mathbf{D}}{\partial t}$$

$$\nabla \cdot \mathbf{D} = \rho$$

$$\nabla \cdot \mathbf{B} = 0$$

The Conservation Equation

$$\nabla \cdot \mathbf{J} + \frac{\partial \rho}{\partial t} = 0$$

Potentials

$$V(\mathbf{r}, t) = \frac{1}{4\pi\epsilon_0} \int \frac{\rho(\mathbf{r}', t - \frac{R}{c})}{R} dv' = \frac{1}{4\pi\epsilon_0} \int \frac{\rho_{ret}}{R} dv'$$

$$\mathbf{A}(\mathbf{r}, t) = \frac{\mu_0}{4\pi} \int \frac{\mathbf{J}(\mathbf{r}', t - \frac{R}{c})}{R} dv' = \frac{\mu_0}{4\pi} \int \frac{\mathbf{J}_{ret}}{R} dv'$$

$$\mathbf{B} = \nabla \times \mathbf{A}$$

$$\mathbf{E} = -\nabla V - \frac{\partial \mathbf{A}}{\partial t}$$

Magnetic Flow Density

$$\mathbf{B}(\mathbf{r}, t) = \frac{\mu_0}{4\pi} \int \frac{\mathbf{J}_{ret} \times \mathbf{e}_R}{R^2} dv' + \frac{\mu_0}{4\pi c} \int \frac{\mathbf{J}'_{ret} \times \mathbf{e}_R}{R} dv'$$

Filamentous Antenna

$$\mathbf{B} = \frac{\mu_0}{4\pi} \int \frac{i(z, t - R/c) d\mathbf{l} \times \mathbf{e}_R}{R^2} + \frac{\mu_0}{4\pi c} \int \frac{i(z, t - R/c) d\mathbf{l} \times \mathbf{e}_R}{R}$$

Oscillating Electric Dipole

$$\mathbf{B} = \frac{\mu_0}{4\pi} \frac{\mathbf{p}'(t - R/c) \times \mathbf{e}_R}{R^2} + \frac{\mu_0}{4\pi c} \frac{\mathbf{p}''(t - R/c) \times \mathbf{e}_R}{R}$$

Oscillating Magnetic Dipole

$$\mathbf{B} = -\frac{\mu_0}{4\pi} \frac{\mathbf{m}'(t - R/c) \times \mathbf{e}_R}{R^2} - \frac{\mu_0}{4\pi c} \frac{\mathbf{m}''(t - R/c) \times \mathbf{e}_R}{R}$$

Pointing's Vector

$$\mathbf{P}_S(\mathbf{r}, t) = \mathbf{E}(\mathbf{r}, t) \times \mathbf{H}(\mathbf{r}, t)$$

Time Harmonic Fields

Planar Sinusoidal Wave

$$\mathbf{E} = \hat{E} \cos(\omega t - \mathbf{k} \cdot \mathbf{r} + \phi) \mathbf{e}_E \quad \text{instantaneous value}$$

$$\mathbf{E} = E_0 e^{-j\mathbf{k} \cdot \mathbf{r}} \mathbf{e}_E \quad \text{complex value}$$

$$E_0 = \hat{E} e^{j\phi} \quad \text{top value scale}$$

$$E_0 = \frac{\hat{E}}{\sqrt{2}} e^{j\phi} \quad \text{effective value scale}$$

Propagation Rate

$$v = \frac{1}{\sqrt{\mu_0 \mu_r \epsilon_0 \epsilon_r}} \quad v = \frac{\omega}{k} \quad k = |\mathbf{k}|$$

Wave Impedance Non-Conductive Space

$$\eta = \sqrt{\frac{\mu_r \mu_0}{\epsilon_r \epsilon_0}}$$

Rule of Right-Hand Systems

$$\mathbf{e}_k = \mathbf{e}_E \times \mathbf{e}_H \quad E = \eta H \quad \mathbf{e}_k = \mathbf{e}_E \times \mathbf{e}_B \quad E = vB$$

Planar Wave in Space with Conductivity

$$\mathbf{E} = E_0 e^{\gamma z} \mathbf{e}_x$$

Complex Propagation Constant

$$\gamma = \sqrt{j\omega\mu_r\mu_0(\sigma + j\omega\epsilon_r\epsilon_0)} \quad \gamma = \alpha + j\beta$$

Waveimpedance, Space With Given Conductivity

$$\eta = \sqrt{\frac{j\omega\mu_r\mu_0}{\sigma + j\omega\epsilon_r\epsilon_0}}$$

Penetration Depth

$$\delta = \sqrt{\frac{2}{\omega\mu_r\mu_0\sigma}}$$

Derivatives

Derivatives

$$\frac{d}{dx} \arcsin(x) = \frac{1}{\sqrt{1-x^2}}$$

$$\frac{d}{dx} \arccos(x) = \frac{-1}{\sqrt{1-x^2}}$$

$$\frac{d}{dx} \arctan(x) = \frac{1}{1+x^2}$$